

# marantz®




## SR6014 9.2CH 4K ULTRA HD AV RECEIVER WITH HEOS BUILT-IN

Drive exquisitely detailed home cinema with the Marantz SR6014 9.2 channel 4K UHD AV receiver. Delight in the most musical sound for any source – from home theatre, to vinyl, to digital streaming. Totally immerse yourself in movies and TV with elevated surround sound formatting from Dolby Atmos, DTS:X and new IMAX Enhanced. Enjoy seamless voice control from the leading voice agents, multi-room connectivity and advanced HDMI technology.

### Highlights

### Your Benefits

9.2 channel AV Receiver with 185W per channel	Enough power to fill bigger rooms with renowned Marantz sound
Built-in WiFi with 2.4GHz/5GHz dual band support; built-in Bluetooth	Improved network stability especially in WiFi-crowded homes
4K/60 Hz full-rate pass-through, 4:4:4 colour resolution, HDR and BT.2020, plus Dolby Vision compatibility and Hybrid Log Gamma (HLG)	Full compatibility with the latest video standards for best picture quality
8 HDMI inputs (incl. 1 front) with full HDCP 2.3 support; 3 HDMI outputs, with 1 HDMI output supporting eARC	Extended connectivity; 2 main zone HDMI outputs + 1 zone output
Analogue to HDMI conversion and full rate 4K Upscaling	Full HD and even Ultra HD video quality from existing video sources
Audyssey MultEQ XT32, Dynamic Volume and Dynamic EQ, LFC, Sub EQ HT	Delivering the most advanced equalization for your individual room
Premium entertainment experience with IMAX Enhanced	New standard for imaging, sound, scale and clarity
Dolby Atmos (up to 7.1.4 with add. 2ch amplifier) and DTS:X	Immersive 3D sound with effects from overhead
Audiophile AKM AK4458 32-bit D/A converters; HDAM; Current Feedback	For the most accurate and detailed audio reproduction
AirPlay 2, Bluetooth, Internet Radio, Spotify Free and Premium, Network Audio Streaming	Access to almost unlimited online music sources
DSD (2.8/5.6MHz), FLAC, ALAC and WAV support	High Resolution audio streaming, even gapless
Integrated high-quality Phono input	Connect your turntable and listen to your beloved Vinyls
HEOS Built-in	Wireless Multi-room audio, voice control and digital music streaming
Extended multi-room capabilities	Enjoy native surround in main room while distributing same source as 2ch downmix in second zone
Colour-coded speaker terminals, Setup Assistant, Marantz AVR Remote App	Hassle-free installation, setup and operation



# because music matters

# marantz®

## SR6014

### 9.2CH 4K ULTRA HD AV RECEIVER WITH HEOS BUILT-IN



Design and specifications are subject to change by Marantz without notice.

FEATURES	SR6014
<b>MULTICHANNEL SURROUND</b>	
DTS HD Master / DTS:X / DTS Neural:X	• / • / •
DTS Virtual:X	•
IMAX Enhanced	•
Dolby TrueHD / Dolby Atmos / Dolby Surround	• / • / •
Multichannel Stereo	•
Compressed audio Enhancer: MDAx2	•
Audyssey	MultEQ XT32 with LFC/Sub EQ HT
Audyssey Dynamic EQ / Dynamic Volume	• / •
Audyssey MultEQ Editor App support	•
<b>NETWORK / SOURCES</b>	
Network Audio Streaming	•
HEOS Multiroom integrated	•
Lossy formats MP3 / WMA / AAC	• / • / •
Lossless formats FLAC / ALAC / WAV	• / • / •
DSD Streaming	(2.8 MHz / 5.6 MHz)
FLAC HD 192/24 / WAV 192/24 / ALAC 192/24	• / • / •
Gapless playback	• (FLAC, WAV, ALAC, DSD)
AirPlay 2	•
Internet Radio (Tuneln)	•
Spotify Connect, Deezer, TIDAL, Napster, Soundcloud *	• / • / • / • / •
Compatible with Remote APP for Smart Phones	Android/iOS
Ethernet / Wi-Fi	• / • (dual antenna / dual band)
Network: (IP-control / update)	• / •
Front Inputs: HDMI / USB	• / •
USB Audio	•
FM / AM Tuner	• / •
Bluetooth	•
Bluetooth Headphone transmission	•
<b>HDMI</b>	
4K 60Hz 4:4:4 resolution / HDCP 2.3	• / •
eARC (Enhanced Audio Return Channel)	•
Dolby Vision compatible / Hybrid Log Gamma (HLG)	• / •
HDMI pass through on stand-by	•
3D video pass through	•
Video conversion	CVBS / HDMI; Comp / HDMI
Videoprocessing and -scaling	1080p, 4K 60/50Hz

\* This feature is not available in all countries.

INPUTS/OUTPUTS		
<b>VIDEO</b>		
Composite In / Out	3+1 / 1	
Component In / Out	2 / 1	
HDMI In / Out	7+1 / 2 main + 1 zone out	
<b>AUDIO</b>		
Analogue In / Out	5+1 / 0 (incl. Phono)	
Digital Optical In	2	
Digital Coaxial In	2	
Multichannel Pre Out	• (11.2 with 11.2 processing)	
Zone audio preout	•	
Subwoofer Out	2	
7.1 Multichannel input	•	
<b>SPECIFICATIONS</b>		
Number of poweramps	9	
Power Output per channel		
6 ohm, 1 kHz, 1%, 1ch Drive	185 W	
6 ohm, 1 kHz, 0.7%, 2ch Drive	150 W	
8 ohm, 20 Hz - 20 kHz, 0.08%, 2ch Drive	110 W	
Audio Signal to Noise Ratio	102 dB	
<b>GENERAL</b>		
Available colours: Black / Silvergold	• / •	
System Remote Control	RC035SR	
Power Consumption in W	680	
Power Consumption No-Sound (ECO ...on/off) in W	50 / 80	
Standby Consumption in W	0.2 (with CEC 0.5)	
Maximum Dimensions (W x D x H) in mm	440 x 398 x 161	
Dimensions packed (W x D x H) in mm	537 x 483 x 257	
Weight in kg	12.8	
Weight packed in kg	15.4	
<b>EAN</b>		
<b>EU</b> SR6014/N1B	4951035069981	Black
SR6014/N1SG	4951035069974	Silvergold
<b>UK</b> SR6014/T1B	4951054070210	Black
SR6014/T1SG	4951055070226	Silvergold

D&M Europe B.V.  
A Division of Sound United  
Beemdstraat 11  
5653 MA Eindhoven  
The Netherlands

www.marantz.eu

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the Symbol, DTS in combination with the Symbol, DTS:X, and the DTS:X logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. The Spotify software is subject to third party licenses found here: [www.spotify.com/connect/third-party-licenses](http://www.spotify.com/connect/third-party-licenses). Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

\* All specs can be subject to change.

[V01]